



MOTOROLA

Chip Errata
DSP56007 Digital Signal Processor
 Mask: 1F91R

ERRATA

Errata Description

Applies
 to Mask

1. Specification timings #83, #84, and #87 in the data sheet provide $1 \times T_C$ less than specified; e.g.,
 - a. specification #83 measures $8 \times T_C$ ($12 \times T_C$) instead of $9 \times T_C$ ($13 \times T_C$) in the EMI fast (slow) DRAM timing mode, respectively;
 - b. specification #84 measures $4 \times T_C - 9$ ($6 \times T_C - 9$) instead of $5 \times T_C - 9$ ($7 \times T_C - 9$) in the EMI fast (slow) DRAM timing mode, respectively; and
 - c. specification #87 measures $4 \times T_C - 15$ ($6 \times T_C - 15$) instead of $5 \times T_C - 15$ ($7 \times T_C - 15$) in the EMI fast (slow) DRAM timing mode, respectively.

1F91R

Workaround: The refresh t_{RAS} timing requirement in a 60 ns DRAM device is not met when the DSP56007FJ66 runs at full speed (66 MHz) and the EMI is programmed in the "fast" DRAM timing mode (EDTM = 0 in ECSR). In this case, only spec timing #84 does not meet the requirement. To ensure correct refresh of a 60 ns DRAM connected to DSP56007FJ66 running at 66 MHz and accessing the DRAM using the EMI fast timing mode, one of the following methods is recommended:

- a. Access the DRAM device without using the internal refresh timer, as described in Section 3.4.1 of the user's manual. This method is possible if the data transfer rate is high.
- b. Refresh the DRAM device in a burst manner, as described in Section 3.4.2.2 of the user's manual. This method divides the real time audio processing window into two portions.

During the first portion, DRAM data transfers without refresh (EREF = 0) are done using the EMI fast timing mode (EDTM = 0).

During the second portion, when EMI is not doing data transfers, a burst of refresh cycles is enabled (EREF = 1) using the EMI slow timing mode (EDTM = 1).



Freescale Semiconductor, Inc.
Chip Errata
DSP56007 Digital Signal Processor
Mask: 1F91R

NOTES

- 1. An over-bar (for example, $\overline{\text{xxxx}}$) indicates an active-low signal.
- 2. The letters seen to the right of the errata tell which DSP56007 mask numbers apply.

-end-