

IMXWNR

i.MX Windows 10 IoT Release Notes

Rev. 1.4.1 — 31 July 2023

Release notes

Document Information

Information	Content
Keywords	i.MX, Windows 10 IoT
Abstract	This document contains important information about the package contents, supported features, known issues and limitations in this release.



1 Overview

i.MX Windows 10 IoT 1.4.0 release includes all necessary code, documents, and tools to assist users in building and running Windows 10 IoT on the i.MX boards from scratch.

Pre-built images are also included for a quick trial on the following platforms:

- i.MX 8M Mini EVK
- i.MX 8M Nano EVK
- i.MX 8M Plus EVK
- i.MX 8M Quad EVK
- i.MX 8QuadXPlus MEK (Silicon Revision C0)
- i.MX 93 EVK

1.1 References

For more information about Windows 10 IoT Enterprise, see [Microsoft online documentation](#).

The following quick start guides available on the [NXP website](#) contain basic information on the board and setting it up:

- [i.MX 8M Quad Evaluation Kit Quick Start Guide](#)
- [i.MX 8M Quad Evaluation Kit Quick Start Guide](#)
- [i.MX 8M Mini Evaluation Kit Quick Start Guide](#)
- [i.MX 8M Nano Evaluation Kit Quick Start Guide](#)
- [i.MX 8M Plus Evaluation Kit Quick Start Guide](#)

Documentation is available online at [nxp.com](#)

1.2 BSP change history

This chapter lists changes in releases including new features and defect fixes.

- 7/2023 W1.4.1
 - **Supported boards:**
 - MCIMX8M-EVK Evaluation Kit
 - 8MMINILPD4-EVK Evaluation Kit
 - 8MNANOLPD4-EVK Evaluation Kit
 - 8MPLUSLPD4-EVK Evaluation Kit
 - MCIM8QXP-MEK (Silicon Revision C0)
 - MCIMX93-EVK (Silicon Revision A0)
 - **New features:**
 - **General**
 - make-winpe-enterprise.cmd: While creating a Windows image, the option for disabling window transparency in GUI is now selected by default. With this change, the script option /

`disable_transparency` was removed, and a new option `/enable_transparency` (for enabling the window transparency) is now supported.

- **Wi-Fi driver:**
 - Wi-Fi board based on 88W8997 SoC is supported. Wi-Fi functionality is enabled.
- **Ethernet (imxnetmini.sys) driver:**
 - PHY initialization engine is updated. Read modify write (MII_REG_RMW) operation of PHY registers is added into the set of commands supported in ACPI table `_DSD ConfigCmds` property.
- **USB in UEFI**
 - USB is enabled in UEFI by default. USB hub, keyboard, mouse, and mass storage devices can be used in UEFI.
- **GPU/display driver:**
 - X86 support: Existing X86 D3D11 apps can now run with GPU acceleration.
 - D3D9 support: A beta D3D9 driver is included. This driver is disabled by default and is intended for customers to test existing WPF apps.
 - Dual-monitor support is added for i.MX 8M Plus (LVDS and HDMI display interfaces).
 - HDMI-audio interface is supported for i.MX 8M Plus.
- **Audio driver:**
 - HDMI-audio driver is added for i.MX 8M Plus (imxaud_hdmi).
- **Fixes:**
 - **Ethernet in UEFI:**
 - MCIMX93-EVK: Ethernet PHY RTL8211FDI-VD-CG initialization sequence in ACPI table is updated.
 - MCIMX93-EVK: Ethernet MAC location in fuses is updated (NET2)
 - **USB in UEFI:**
 - MCIMX8M-EVK: USB Initialization is updated. PHY suspend is disabled (ERR011231).
 - **SPI driver:**
 - The case when a write transfer is sometimes not completed is fixed.
 - Upper limitation `ReferenceClockHz/2` for communication speed is added. `ReferenceClockHz` is specified in ACPI.
 - **GPU/display driver:**
 - 1280x800 resolution with 71 MHz pixel clock is supported in the HDMI and LVDS display clock driver.
 - When IMX-LVDS-HDMI or IMX-MIPI-HDMI converter is used but the monitor is disconnected, the UEFI display driver reports an error and does not initialize the display controller. It is fixed, now the UEFI driver initializes to the default resolution when the monitor is disconnected from the converter.
- 3/2023: W1.4.0
 - **Supported boards:**
 - MCIMX8M-EVK Evaluation Kit
 - 8MMINILPD4-EVK Evaluation Kit
 - 8MNANOLPD4-EVK Evaluation Kit
 - 8MPLUSLPD4-EVK Evaluation Kit
 - MCIM8QXP-MEK (Silicon Revision C0)
 - MCIMX93-EVK (Silicon Revision A0)
 - **New features:**
 - **General**
 - 8MPLUSLPD4-EVK: The size of SDRAM was increased to 6 GB. Note: This change requires `windows10.0-kb5019275-arm64_c6c2abc31137d43e762304bd1542ba413d2b8b9e.msu` to be installed. The patch is applied in installation script (`make-winpe-enterprise.cmd`) by default.
 - U-Boot updated to version 2022.04-00346.
 - ATF updated to version v2.6.

- The CPU core count in ACPI (Dsd-Platform.asl) is controlled by the PcdCoreCount setting now.
- `make-winpe-enterprise.cmd`: A mechanism for the application of updates to the Windows image is added, see Quick Start Guide for details.
- `make-winpe-enterprise.cmd`: The `/patch_sdport` parameter was removed. There is an updated version of the system "sdport.sys" driver in windows10.0-kb5019275-arm64_c6c2abc31137d43e762304bd1542ba413d2b8b9e.msu patch. The patch is applied in the installation script (`make-winpe-enterprise.cmd`) by default.
- `flash-bootloader.cmd`: Support for abbreviations of board names is added.
- **Power Management**
 - The Deepest Runtime Idle Platform State (DRIPS) is supported, see `powercfg /sleepstudy`.
- **Audio driver:**
 - A new Wm8962codec driver is added to support the WM8962 device.
- **SPI driver:**
 - A new imxlpspi driver is added to support the LPSPI IP block.
- **Camera driver:**
 - A new MIPI CSI-2 DWC driver is added into BSP to enable video capture on i.MX 93.
 - A new driver for the X-RPI-CAM-MIPI camera board (AP1302 ISP + AR0144 camera) is added to enable video capture on i.MX 93.
- **Malone VPU driver:**
 - A new Malone VPU driver for hardware accelerated video decoding is added. Supported codecs: H264, H265, VP8, MPEG2, MPEG4.
- **GPU/display driver:**
 - Support of rotated modes and display modes smaller than the native mode for HDMI monitor on i.MX 8M Plus.
 - The IMX-DSI-OLED1 panel driver is added to the MIPI-DSI driver for i.MX 8M Nano.
 - The display controller and display interface are disabled when entering power down mode and enabled upon wakeup.
 - UEFI display driver is supported for i.MX 93. Supported displays:
 - MIPI-DSI with Mipi2Hdmi display bridge supporting resolution up to 1080p.
 - LVDS panel BOE ev121wxm-n12 with fixed resolution 1280x800.
- **IMU driver:**
 - A new IMU sensor driver is added. It combines the Linear accelerometer and the Gyroscope sensor.
- **FlexCAN driver:**
 - The FlexCAN device is supported on i.MX 93.
- **UART driver:**
 - LPUART is supported for i.MX 93 in interrupt mode. No flow control pins are available.
 - RTS-CTS flow control is enabled for UART3 on i.MX 8M\Mini\Nano\Plus.
- **Fixes:**
 - **GPU/display driver:**
 - Performance of NV12 format processing on i.MX 8M Plus and i.MX 8M Nano is improved to make video playback performance better.

- i.MX 8M Plus: 85.5 MHz and 65 MHz pixel clocks added to HDMI to support 1366x768@60 and 1024x768@60 resolutions.
- **Audio driver:**
 - Fixed "DPC execution time exceeds system limit" assertion when the microphone is used.
- **I2C driver:**
 - Fixed a memory leak at unloading imxlp2c driver related to ACPI Dsd Buffer allocation.
- 12/2022: W1.3.0
 - **Supported boards:**
 - MCIMX8M-EVK Evaluation Kit
 - 8MMINILPD4-EVK Evaluation Kit
 - 8MNANOLPD4-EVK Evaluation Kit
 - 8MPLUSLPD4-EVK Evaluation Kit
 - MCIM8QXP-MEK (Silicon Revision C0)
 - **New features:**
 - **General**
 - UEFI.fit image is merged to U-Boot FIT image on 8M platforms.
 - UEFI binary is compressed before inserted to uefi.fit on 8M platforms.
 - The firmware name is suffixed with "_uuu" if it is compiled with UUU tools.
 - Removed "-t signed". The firmware is always signed when using "-t secured_efi".
 - Custom HAB/AHAB signing keys can be now used by defining the "KEY_ROOT" path.
 - **Audio driver:**
 - Driver `imxaud.sys` has been split into `imxaud.sys` using multi-channel SAI peripheral for i.MX 8M and `imxaudsc.sys` using single-channel SAI peripheral for i.MX 8QXP.
 - **I2C driver:**
 - A new `imxlp2c` driver for the LPI2C peripheral is included. Interrupt and polling modes have been supported.
 - A new `iMXLpi2cLib` driver for the LPI2C peripheral in UEFI is included.
 - **ENET driver:**
 - QoS driver is supported on i.MX 8M Plus.
 - **I2C sensor drivers:**
 - e-Compass FXOS8700 - Accelerometer and Magnetometer is supported on the i.MX 8QXP MEK board.
 - Gyroscope FXAS2100 is supported on the i.MX 8QXP MEK board.
 - Ambient Light Sensor ISL29023 is supported on i.MX 8QXP MEK board.
 - **GPU/display driver:**
 - GPU driver is added for i.MX 8QXP.
 - HDMI display interface is supported for i.MX 8M Plus.
 - GPU driver version is increased to 1.4.
 - GPU driver support for video processing is added for i.MX 8M Nano/Plus.
 - The source code for the GPU driver kernel part (galcore) is included in the BSP.
 - **UART driver:**
 - LPUART is supported for i.MX 8QXP in interrupt mode. No flow control is available for LPUART0 and LPUART2. LPUART1 (m2 slot) has RTS, CTS pins wired.
- **Fixes:**
 - **GPU/display driver:**
 - Unsupported resolution and pixel clock (for example 1280x800, pclk=68.9 MHz) display an error message. As a workaround, the algorithm was changed to set the closest possible pixel clock and display a warning message.

- i.MX 8M: Resolution 720p is set by default when a display is not connected or it does not support EDID.
- **USBC:**
 - i.MX 8M Plus: USB 3.0 devices were incorrectly detected as USB 2.0. USB Type-C multiplex/demultiplexer switch "Selection control" pin polarity setting has been added to the ACPI table.
- 10/2022: W1.2.1
 - **New features:**
 - **Wi-Fi and Bluetooth driver:**
 - Wi-Fi AzureWave AW-CB178NF board based on 88W8897 SoC has been supported. Wi-Fi and Bluetooth functionality has been enabled.
- 8/2022: W1.2.0
 - **Supported boards:**
 - MCIMX8M-EVK evaluation kit
 - 8MMINILPD4-EVK evaluation kit
 - 8MNANOD4-EVK evaluation kit
 - 8MPLUSLPD4-EVK evaluation kit
 - **New features:**
 - **General**
 - [Visual Studio 2019](#) has been supported, but version 2017 is no longer supported.
 - Firmware update: buildme64.sh switch –cap added to build the Firmware capsule. Capsule update working from UEFI shell with capsule stored on SD card: fs0: CapsuleApp.efi fs3: FirmwareCapsuleIMX.cap
 - make-winpe-enterprise.cmd parameters have been updated, see [User's Guide](#) for details.
 - i.MX 8M CPU frequency changed from 1 GHz to 1.5 GHz
 - **GPU driver:**
 - GPU driver has been updated to v1.3.
 - GPU driver added for i.MX 8M Plus and i.MX 8M Nano SOCs.
 - GPU driver support for video processing has been added for i.MX 8M.
 - **Camera driver:**
 - OV5640 camera has been supported for all EVK boards.
 - OV10635 camera has been supported for all EVK boards.
 - YUV422 YUY2 and YUV420 NV12 camera color formats have been supported. The i.MX 8M EVK does not support YUV420 NV12 format.
 - **Display driver:**
 - Windows driver with fixed display mode supported for LVDS display interface for i.MX 8M Plus.
 - Windows driver with fixed display mode supported for MIPI-DSI display interface for i.MX 8M Nano.
 - **VPU driver:**
 - VPU decoder has been supported for i.MX 8M Quad, i.MX 8M Mini, and i.MX 8M Plus EVK boards.
 - **Fixes:**
 - **WM8960 driver:** I2C is correctly released when the WM8960 device is removed.
- 6/2022: W1.1.0
 - Public release for i.MX 8M Nano and i.MX 8M Plus platforms.
 - **Supported boards:**
 - MCIMX8M-EVK evaluation kit
 - 8MMINILPD4-EVK evaluation kit
 - 8MNANOD4-EVK evaluation kit

- 8MPLUSLPD4-EVK evaluation kit
- **New features:**
 - **Camera driver:** OV5640 camera in J1502 connector has been supported on i.MX 8M EVK board.
 - **FlexCAN driver:** FlexCAN device has been supported on i.MX 8M Plus EVK by the imxcan.sys driver.
 - **I2C driver:** I2C expander (PCA6416) has been supported in iMX8BoardInit module and options `SelectCAN1InsteadOfI2C5` and `SelectCAN2InsteadOfPDMStream3` allow configuring corresponding selectors on the Base Board.
 - **GPU driver:** GPU driver has been updated to v1.1.
 - **Debug drivers:** WinDbg over Ethernet has been supported. WinDbg over Ethernet requires the `kd_8003_1fc9.dll` library which is not distributed as a part of the BSP. To get this library, contact Microsoft.
 - **ENET driver:** HW checksum offload has been supported in the NDIS miniport driver.
- **Fixes:**
 - **Audio driver:** A failure during uninstallation in the Device manager has been fixed.
 - **Display driver:** IMX-LVDS-HDMI and IMX-MIPI-HDMI converters: If a native HDMI display resolution exceeds the upper limit, the fixed maximum available resolution is set instead. 1920x1080@60 Hz in case of IMX-MIPI-HDMI and 1280x720@60 Hz in case of IMX-LVDS-HDMI.
 - **SD driver:** Configuration “fixed device” has been changed to “removable device”, which allows you to safely remove the SD card by the "Eject" option.
- 4/2022: W1.0.0
Public release for i.MX 8M and i.MX 8M Mini platforms.
 - **Supported boards:** MCIMX8M-EVK evaluation kit 8MMINILPD4-EVK evaluation kit
 - **New features:**
 - **VPU driver:** Supported codecs HEVC, VP9, H.264, VP8. MPEG-2 and MPEG-4 codecs supported on i.MX 8M only.
 - **Fixes:**
 - **UART driver:** The UART driver failure during uninstallation in the Device manager has been fixed.
 - **I2C driver:** The issue in iMXI2cRead function (when ReadBufferSize == 1) in UEFI has been fixed.
 - **buildme 64.sh:** The script has been updated. Updates in UEFI source code were included in firmware.bin only if firmware was built with -c parameter (clean build).
 - **PCIe:** PCIe ATU (Address Translation Unit) setup for PCIe BAR memory-mapped registers in UEFI drivers has been fixed. After this fix, the system works as expected in UEFI and relevant Storage drivers appear in Windows.
- 3/2022: W0.9.1
Public preview release for i.MX 8M platform.
 - **Fixes:**
 - **eMMC driver:** eMMC tuning parameters add to the Dsdt-Sdhc.asl.
 - **BSP deployment:** Removed invalid characters from make-winpe-enterprise.cmd.
- 1/2022: W0.9.0
Private preview release for i.MX 8M platform.
 - **Supported boards:** The existing BSP with support for the MCIMX8M-EVK NXP board.

2 BSP supported features

The following table displays the features supported in this BSP release. If no board is explicitly mentioned, the feature is shared across all boards listed in Supported Hardware in the Release contents section; otherwise, the feature is only supported on the boards listed.

Board name	Board revision	Schema revision	BSP name
MCIMX8M-EVK	700-38820 REV A	SCH-38820 REV A2	MX8M_EVK
8MMINILPD4-EVK	700-31407 REV A3 (base board)	SCH-31407 REV C4 (base board)	MX8M_MINI_EVK
	700-47712REV X2 (cpu board)	SCH-47712 REV A2 (cpu board)	
8MNANOLPD4-EVK	700-31407 REV X5 (base board)	SCH-31407 REV C2 (base board)	MX8M_NANO_EVK
	700-38823 REV A (cpu board)	SCH-38823 REV A2 (cpu board)	
8MPLUSLPD4- EVK	700-46370 REV B (base board)	SCH-46370 REV B1 (base board)	MX8M_PLUS_EVK
	700-46368 REV A (cpu board)	SCH-46368 REV A3 (cpu board)	
MCIM8QXP-MEK	700-29683 REV C2 (cpu board)	SCH-29683 REV D5 (cpu board)	MX8QXP_MEK
	700-29918 REV C1 (base board)	SCH-29918 REV C1 (base board)	
MCIMX93-EVK	700-51943 REV X2 (cpu board)	SCH-51943 REV B (cpu board)	MX93_11X11_EVK
	700-51961 REV X7 (base board)	SCH-51961 REV B (base board)	

Feature	Supported board	Comment
Boot Image		
U-Boot	All i.MX	- Clock, Anaport regulator, ENET, UART, MMC/SD, eMMC4.3/4.4/4.5.
OP-TEE	All i.MX	- OP-TEE OS is required on the boot partition with the TEE file for OP-TEE enablement.
Machine-specific layer		
Interrupt	All i.MX	- GIC
Clock	All i.MX	- Controls the system frequency and clock tree distribution.
Timer	All i.MX	- System timer tick and broadcast timer support.
GPIO	All i.MX	- GPIO is initialized in earlier phase according to hardware design.
IOMUX	All i.MX	- Provides the interfaces for I/O configuration.
SCFW	i.MX 8QXP	- Clock/Power/Security is controlled by the "System Control Firmware". The "imxscfw" driver controls communication channel with this firmware.

Feature	Supported board	Comment
DMA engine		
SDMA	i.MX 8M	- SDMA HAL
Character device drivers		
UART	i.MX 8M/Mini/Nano/Plus	- DMA (default) and Interrupt mode is configurable in ACPI - UART2 is not available in Windows, used by the Cortex-M4 processor.
LPUART	i.MX 8QXP/93	- Interrupt mode
Networking drivers		
ENET	All i.MX	- i.MX 8 supports Atheros AR8031 PHY with 10/100/1000 bps mode
ENET QOS	i.MX 8M Plus	- ENET QOS is available on i.MX 8M Plus. - RTL8211 PHY is supported.
PCIe	All i.MX	- i.MX 8 supports M.2 interface.
Sound drivers		
SAI	All i.MX	- Supports both transmit to and receive from the audio codec.
WM8524 codec	i.MX 8M/Mini/Nano	- Supports playback
WM8960 codec	i.MX 8M Plus/8QXP	- Supports playback and record.
WM8962 codec	i.MX 93	- Supports playback and record.
HDMI audio	i.MX 8M Plus	- Supports playback. HDMI device must be audio capable.
USB drivers		
USB Host	All i.MX	- Supports USB-A and USB-C connectors.
Display/GPU		
HDMI	i.MX 8M/Plus	- Up to 1080p
LVDS display interface	i.MX 8M Plus/8QXP	i.MX 8M Plus: - Single-channel mode up to 720p - Dual-channel mode up to 1080p (or 1920x1200@60 Hz) - Default mode set to 720pi.MX 8QXP: - Single-channel mode up to 1080p - Default mode set to 1080p
IMX-LVDS-HDMI (LVDS to HDMI converter)	i.MX 8M Plus.i.MX 8QXP	- Single-channel mode. Default resolution – see above.
MIPI-DSI display interface	i.MX 8M Mini/Nano	- i.MX 8M Nano: supports Windows GPU driver up to 1080p (or 1920x1200@60 Hz). Default resolution set to 720p.- i.MX 8M Mini: no Windows driver, only firmware support up to 1080p. Default resolution with IMX-MIPI-HDMI converter depends on the monitor native mode – 1080p in most cases.

Feature	Supported board	Comment
IMX-MIPI-HDMI (MIPI-DSI to HDMI converter)	i.MX 8M Mini/Nano	- Default resolution – see above.
GPU	i.MX 8M/Plus/Nano/8QXP	- HW acceleration for 3D rendering through D3D11 API, therefore accelerates D2D, XAML, UWP, WinUI, Windows desktop UI, and D3D11 apps.
Multiple displays	i.MX 8M Plus	- i.MX 8M Plus: HDMI and LVDS.
Camera		
Camera (SoCs with CSI Bridge)	i.MX 8M/Mini	- Video preview at 720p 30 fps YUYV.
Camera (SoCs with ISI)	i.MX 8M Plus/Nano	- Video preview at 720p 30 fps YUYV and NV12
OV5640 camera	All i.MX	- Second camera configurable in UEFI in <BOARD>.dsc file.
OV10635 camera	All i.MX	- Selectable in UEFI in <BOARD>.dsc file.- i.MX 8M/Mini/Nano/Plus requires an external 12 V PSU and a manual reset every time Windows OS is rebooted.- i.MX 8QXP powers camera via mini SAS connector.
X-RPI-CAM-MIPI camera	i.MX 93	
Video		
VPU full feature	i.MX 8M	- Supported codecs HEVC, VP9, H.264, VP8, MPEG-2, and MPEG-4 codecs
VPU limited feature	i.MX 8 Mini/Plus	- Supported codecs HEVC, VP9, H.264, VP8.
General drivers		
uSDHC	All i.MX	- Supports SD, SDXC, eMMC.
I2C	All i.MX	- Supports I2C master mode.
SPI	All i.MX	- Supports SPI master mode.
FlexCAN	i.MX 8M	- FlexCAN low-level driver.
RTC	i.MX 8M/Mini/Nano/Plus	- Basic Set/GetTime UEFI support, reset/battery time retention.
Power management		
Device power management	All i.MX	- Sample PoFx callbacks are implemented in i2c and pwm drivers. Devices entering D3 (power down) and D0 (active) states, WakeUp sample callbacks in i2c driver.
Processor power management	All i.MX	- PEP (Power Engine Plugin) driver is included in this release. Set usePpm to 1 in imxpep.cpp to enable processor power management, and contact NXP for the latest Pep version.
USB Power delivery	All i.MX	- The initial USB Power delivery contract is negotiated in Uboot. See <code>tcpc_port_config</code> structure

Feature	Supported board	Comment
		initialization in imx8mp_evk.c, imx8mq_evk.c, imx8mm_evk.c, and imx8mn_evk.c files for actual setting of voltage and current for given board.
Power button shutdown	8M/Mini/Nano	- Short pressing of the power (ONOFF) button on the EVK boards initiates the graceful WinOS shutdown. Long pressing >5sec of the power (ONOFF) button initiates the immediate emergency power-off
8M Nano overdrive	8M Nano	- PcdPmicOverDriveEnable setting in firmware's MX8M_NANO_EVK. dsc increases Nano CPU 1.2GHz to 1.4GHz, GPU 400 MHz to 600 MHz. Using Nano overdrive requires passive CPU cooler or thermal management driver

3 Known issues/limitations

Read through all hardware-related reference material and ensure that you have made all the necessary hardware modifications before using the software.

Limitation/Workaround	SoC
Boot	
Limitation: Supported boot media are SD and eMMC only. Workaround: No workaround.	All
UEFI	
Limitation: Non-volatile (NV) non-authorized UEFI variables are not persistent after reboot. Workaround: No workaround.	All
Camera	
Limitation: Only i.MX 8MQ EVK SCH-29615 rev. B4 is supported. Earlier board revisions use different I2C for the camera. Workaround: For i.MX 8MQ EVK SCH-29615 rev. B3, choose I2C1 camera device instead of I2C2 in <code>mu_platform_nxp/NXP/<BOARD>/AcpiTables/Dsdt_Camera_<CONFIGURATION>.asl</code> .	i.MX 8M
Limitation: OV10635 requires an external 12V power source and cannot be reconfigured by software without a power cycle. Workaround: After powering off the board, unplug the power supply from the camera and wait a few seconds before powering the camera and EVK board again.	i.MX 8Mi.MX 8M Mini i.MX 8M Nano i.MX 8M Plus
Display/GPU	
Limitation: Some monitors/displays may fail reading EDID using on board HDMI interface because of incompatible voltage level shifter on 8MPLUSLPD4-EVK revision A. Workaround: Use 8MPLUSLPD4-EVK revision B1 or newer.	i.MX 8M Plus

Limitation/Workaround	SoC
Limitation: GPU driver support of D3D9 is disabled by default. Workaround: GPU D3D9 driver can be enabled by updating registers value: <code>reg add "HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Control\Class\{4d36e968-e325-11ce-bfc1-08002be10318}\0000" /v UserModeDriverName /t REG_MULTI_SZ /d umd9.dll\0umd11.dll\0umd11.dll\0umd12.dll /f</code> <code>reg add "HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Control\Class\{4d36e968-e325-11ce-bfc1-08002be10318}\0000" /v UserModeDriverNameWow /t REG_MULTI_SZ /d umd9.dll\0umd11.dll\0umd11.dll\0umd12.dll /f</code> <code>reg add "HKEY_LOCAL_MACHINE\SYSTEM\CurrentControlSet\Control\Class\{4d36e968-e325-11ce-bfc1-08002be10318}\0000" /v UserModeDriverNameWow2 /t REG_MULTI_SZ /d umd9.dll\0umd11.dll\0umd11.dll\0umd12.dll /f</code>	i.MX 8M i.MX 8M Plus i.MX 8M Nano i.MX 8QXP
Limitation: Using Remote Desktop to connect to the device results in black screen. Workaround: Apply the following register value to run the older XDDM driver for Remote Desktop: <code>reg add "HKLM\System\CurrentControlSet\Control\Terminal Server\WinStations" /v "LoadWddmIDDDriver" /t REG_DWORD /d 0x0 /f</code>	i.MX 8M
GPIO	
Limitation: EXP_IO pins on EXP CN connector cannot be used as GPIOs because they are connected to PCA6416 I/O expander for which there is no driver implemented. Workaround: Use the GPIO pin on the EXP CN connector connected directly to the SoC's pin with GPIO functionality instead of connecting to the PCA6416 I/O expander.	i.MX 8M Mini i.MX 8M Nano i.MX 8M Plus
SDHC	
Limitation: The <code>imxusdhc.sys</code> in crash dump mode does not read HW-specific settings from ACPI so these values are hardcoded in the <code>SdhcSlotInitialize()</code> method. Workaround: Keep these values synchronized with values in <code>Dsdt-Sdhc.asl</code> ACPI table.	All
Limitation: SDCARD insertion/removal can cause a bug check if the delay between insertion/removal is too short. Workaround: Wait a few seconds before insertion/removal.	All
UART/LPUART	
Limitation: The RTS-CTS hardware flow control is not available for all UARTs. Workaround: Use UART with routed RTS-CTS pins.	All
USB	
Limitation: The size of SDRAM was increased to 6 GB. This change requires <code>windows10.0-kb5019275-arm64-c6c2abc31137d43e762304bd1542ba413d2b8b9e.msu</code> to be installed. Workaround: The patch is applied in installation script (<code>make-winpe-enterprise.cmd</code>) by default.	i.MX 8M Plus
PCIe	

Limitation/Workaround	SoC
Limitation: PCIe DMA supports 32-bit addressing only. Connected PCIe devices using memory > 4GB may work incorrectly. Workaround: Allocate memory for PCIe devices below 4G or copy data to lower address space in the device driver.	i.MX 8M i.MX 8M Mini i.MX 8M Plus i.MX 8QXP
VPU	
Limitation: All MScale SoC's (hantro VPU) decoding attempts could fail, due to runtime requirements of physical contiguous memory. This memory may not be available because of RAM fragmentation. Workaround: Reboot the board and play video on the freshly booted system.	i.MX 8M i.MX 8M Mini i.MX 8M Plus

4 Revision history

Revision number	Date	Substantive changes
W0.9.0	1/2022	Private preview release for i.MX 8M platform.
W0.9.1	3/2022	Public preview release for i.MX 8M platform.
W1.0.0	4/2022	Public release for i.MX 8M and i.MX 8M Mini platforms.
W1.1.0	6/2022	Public release for i.MX 8M Nano and i.MX 8M Plus platforms.
W1.2.0	9/2022	Sections 1.2 and 3 are updated.
W1.2.1	10/2022	Section 1.2 is updated.
W1.3.0	12/2022	i.MX 8QuadXPlus MEK board support added.
W1.4.0	3/2023	i.MX 93 EVK board support added.
W1.4.1	7/2023	Section 1.2 is updated.

5 Legal information

5.1 Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

5.2 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Suitability for use in non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at PSIRT@nxp.com) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

NXP B.V. - NXP B.V. is not an operating company and it does not distribute or sell products.

5.3 Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners.

NXP — wordmark and logo are trademarks of NXP B.V.

Contents

1 Overview 2

1.1 References2

1.2 BSP change history2

2 BSP supported features 7

3 Known issues/limitations 11

4 Revision history 13

5 Legal information 14

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.