

				
25	PTA1/UART0_RX/FTM0_CH6/JTAG_TDI/EZP_DI	VBAT	25	
28	PTA2/UART0_TX/FTM0_CH7/JTAG_TDO/TRACE_SWO/EZP_DO	VDD1	7	
29	PTA3/UART0_RTS/FTM0_CH0/JTAG_TMS/SWD_DIO	VDD2	38	
30	PTA4/LLWU_P3/FTM0_CH1/NMI/EZP_CS	VDD3	60	
31	PTA5/FTM0_CH2/I2S0_TX_BCLK/JTAG_TRST			
32	PTA12/FTM1_CH0/I2S0_TXD0/FTM1_QD_PHA	VDDA	17	
33	PTA13/LLWU_P4/FTM1_CH1/I2S0_TX_FS/FTM1_QD_PHB			
34	PTA14/SPI0_PCS0/UART0_TX/I2S0_RX_BCLK/I2S0_TXD1	VREFH	18	
35	PTA15/SPI0_SCK/UART0_RX/I2S0_RXD0			
36	PTA16/SPI0_SOUT/UART0_CTS/UART0_COL/I2S0_RX_FS/I2S0_RXD1			
37	PTA17/SPI0_SIN/UART0_RTS/I2S0_MCLK	VREF_OUT/CMP1_IN5/CMP0_IN5	21	
40	PTA18/EXTAL0/FTM0_FLT2/FTM_CLKIN0			
41	PTA19/XTAL0/FTM1_FLT0/FTM_CLKIN1/LPTMR0_ALT1			
43	PTB0/LLWU_P5/ADC0_SE8/I2C0_SCL/FTM1_CH0/FTM1_QD_PHA			
44	PTB1/ADC0_SE9/I2C0_SDA/FTM1_CH1/FTM1_QD_PHB			
45	PTB2/ADC0_SE12/I2C0_SCL/UART0_RTS/FTM0_FLT3			
46	PTB3/ADC0_SE13/I2C0_SDA/UART0_CTS/UART0_COL/FTM0_FLT0	ADC0_DP0	13	
47	PTB10/SPI1_PCS0/UART3_RX/FTM0_FLT1	ADC0_DM0	14	
48	PTB11/SPI1_SCK/UART3_TX/FTM0_FLT2			
49	PTB12/UART3_RTS/FTM1_CH0/FTM0_CH4/FTM1_QD_PHA	ADC0_DP3	15	
50	PTB13/UART3_CTS/FTM1_CH1/FTM0_CH5/FTM1_QD_PHB	ADC0_DM3	16	
51	PTB16/SPI1_SOUT/UART0_RX/EWM_IN/FTM_CLKIN0			
52	PTB17/SPI1_SIN/UART0_TX/EWM_OUT/FTM_CLKIN1	DAC0_OUT/CMP1_IN3/ADC0_SE23	22	
53	PTB18/FTM2_CH0/I2S0_TX_BCLK/FTM2_QD_PHA			
54	PTB19/FTM2_CH1/I2S0_TX_FS/FTM2_QD_PHB			
55	PTC0/ADC0_SE14/SPI0_PCS4/PDB0_EXTRG/I2S0_TXD1			
56	PTC1/LLWU_P6/ADC0_SE15/SPI0_PCS3/UART1_RTS/FTM0_CH0/I2S0_TXD0	RESET	42	
57	PTC2/ADC0_SE4B/CMP1_IN0/SPI0_PCS2/UART1_CTS/FTM0_CH1/I2S0_TX_FS			
58	PTC3/LLWU_P7/CMP1_IN1/SPI0_PCS1/UART1_RX/FTM0_CH2/I2S0_TX_BCLK			
61	PTC4/LLWU_P8/SPI0_PCS0/UART1_TX/FTM0_CH3/CMP1_OUT			
62	PTC5/LLWU_P9/SPI0_SCK/LPTMR0_ALT2/I2S0_RXD0/CMP0_OUT/FTM0_CH2			
63	PTC6/LLWU_P10/CMP0_IN0/SPI0_SOUT/PDB0_EXTRG/I2S0_RX_BCLK/I2S0_MCLK	EXTAL32	24	
64	PTC7/CMP0_IN1/SPI0_SIN/I2S0_RX_FS	XTAL32	23	
65	PTC8/CMP0_IN2/I2S0_MCLK			
66	PTC9/CMP0_IN3/I2S0_RX_BCLK/FTM2_FLT0			
67	PTC10/I2C1_SCL/I2S0_RX_FS			
68	PTC11/LLWU_P11/I2C1_SDA/I2S0_RXD1			
69	PTC12			
70	PTC13			
71	PTC16/UART3_RX			
72	PTC17/UART3_TX			
73	PTD0/LLWU_P12/SPI0_PCS0/UART2_RTS			
74	PTD1/ADC0_SE5B/SPI0_SCK/UART2_CTS			
75	PTD2/LLWU_P13/SPI0_SOUT/UART2_RX/I2C0_SCL			
76	PTD3/SPI0_SIN/UART2_TX/I2C0_SDA			
77	PTD4/LLWU_P14/ADC0_SE21/SPI0_PCS1/UART0_RTS/FTM0_CH4/EWM_IN			
78	PTD5/ADC0_SE6B/SPI0_PCS2/UART0_CTS/UART0_COL/FTM0_CH5/EWM_OUT			
79	PTD6/LLWU_P15/ADC0_SE7B/SPI0_PCS3/UART0_RX/FTM0_CH6/FTM0_FLT0			
80	PTD7/ADC0_SE22/CMT_IRO/UART0_TX/FTM0_CH7/FTM0_FLT1			
1	PTE0/ADC0_SE10/SPI1_PCS1/UART1_TX/TRACE_CLKOUT/I2C1_SDA/RTC_CLKOUT	VSS1	8	
2	PTE1/LLWU_P0/ADC0_SE11/SPI1_SOUT/UART1_RX/TRACE_D3/I2C1_SCL/SPI1_SIN	VSS2	39	
3	PTE2/LLWU_P1/ADC0_DP1/SPI1_SCK/UART1_CTS/TRACE_D2	VSS3	59	
4	PTE3/ADC0_DM1/SPI1_SIN/UART1_RTS/TRACE_D1/SPI1_SOUT			
5	PTE4/LLWU_P2/SPI1_PCS0/UART3_TX/TRACE_D0	VSSA	20	
6	PTE5/SPI1_PCS2/UART3_RX			
9	PTE16/ADC0_SE4A/SPI0_PCS0/UART2_TX/FTM_CLKIN0/FTM0_FLT3	VREFL	19	
10	PTE17/ADC0_SE5A/SPI0_SCK/UART2_RX/FTM_CLKIN1/LPTMR0_ALT3			
11	PTE18/ADC0_SE6A/SPI0_SOUT/UART2_CTS/I2C0_SDA			
12	PTE19/ADC0_SE7A/SPI0_SIN/UART2_RTS/I2C0_SCL			

<Value>